

Meter - Pack for Self Contained Meters **



**** A main disconnect switch is required for over 6 meters served by a single service.**

100 Amp, 4-Terminal, OH/UG, Ringless, Aluminum

2 - Sockets

Landis & Gyr: UA2331-OG
Square D: UAT-2R1121C-SQD
Cutler-Hammer: UATZ2R1121C-FLCH

3 - Sockets

Landis & Gyr: UA3331-OG
Square D: UAT-3R1121C-SQD
Cutler-Hammer: UATZ3R1121C-FLCH

4 - Sockets

Landis & Gyr: UA4331-OG
Square D: UAT-4R1121C-SQD
Cutler-Hammer: UATZ4R1121C-FLCH

5 - Sockets

Square D: UAT-5R1121C-SQD
Cutler-Hammer: UATZ5R1121C-FLCH

6 - Sockets

Square D: UAT-6R1131C-SQD
Cutler-Hammer: UATZ6R1131C-FLCH

200 Amp, 4-Terminal, OH/UG, Ringless, Aluminum

2 - Sockets

Milbank: UAP1252-X-HSP
Landis & Gyr: UA2736-ZGF
Square D: UAT-2R2332U-SQD
Cutler-Hammer: UAT2R2332U-FLCH

3 - Sockets

Milbank: UAP1253-X-HSP
Landis & Gyr: UA3737-ZGF
Square D: UAT-3R2332U-SQD
Cutler-Hammer: UAT3R2332U-FLCH

4 - Sockets

Milbank: UAP1254-X-HSP
Landis & Gyr: UA4739-ZGF
Square D: UAT-4R2352U-SQD
Cutler-Hammer: UAT4R2352U-FLCH

5 - Sockets

Milbank: UAP1255-X-HSP
Landis & Gyr: UA5739-MGF
Square D: UAT-5R2392UU-SQD
Cutler-Hammer: UAT5R2392UU-FLCH

6 - Sockets

Milbank: UAP1256-X-HSP
Landis & Gyr: UA6739-MGF
Square D: UAT-6R2392UU-SQD
Cutler-Hammer: UAT6R2392UU-FLCH

Notes:

1. - All Meter Sockets provided and installed by customer at site approved by BPUB.
2. - All Meter Sockets are to be new stock and UL listed.
3. - Meter and Service installations must also meet City of Brownsville or Cameron County inspection requirements.
4. - 7-Terminal Steel Meter-Packs must be UL listed or have a Texas Professional Engineer's Seal on the specifications.



BROWNSVILLE
PUBLIC UTILITIES BOARD

METER - PACK

DEVELOPED BY:

STANDARDS
COMMITTEE

APPROVED

Sep 2020

DRAWING
NUMBER

ENG - 6A

